系统安装说明

系统盘制作工具下载地址:

http://www.yelighting.com/download/Win32DiskImager.rar

1.打开 Win32DiskImager 工具,工具会自动选择空盘。

👒 Win32 Disk Imager	
Image File	Device
	[I:\] ▼
Copy MD5 Hash: Progress	
Version: 0.9.5 Cancel Read Wr	ite Exit
	ii.

2.点击文件夹图标选择系统文件

🎭 Win32 Disk Imager			
Image File	Devic	ze	
Copy MD5 Hash:			
Progress			
Version: 0.9.5 Cancel Read	Write Exit		
Select a disk image			×
😋 🕞 🗣 📜 « Pcie 🕨 FCS-3.2.2.13-UP-R33	▼ 4 3	搜索 FCS-3.2.2.13-UF	P-R33 🔎
组织 ▼ 新建文件夹			
图片	<u>^</u>	修改日期	类型
🖹 文档 🚺 FCS-3.2.2.13-U	IP-R33.img	2016/10/27 19:2	1 IMG 文件
♪ 音乐	-		
口 异//1 ▲ 本地磁曲 (C:)			
本地磁盘 (D:) ■			
本地磁盘 (E:)			
🕞 本地磁盘 (F:)			
本地磁盘 (G:)			
可移动磁盘 (T:) ▼ ◆			
文件名(N):	-	Disk Images (*.img *.I	MG) 🔫
		打开(0)	取消

3.点击 write 进行烧写,点击确认.

😼 Win32 Disk Imager	
Image File	Device
F:/Pcie/FCS-3.0.0.5-VP-R17.img	[I:\] 🔻
Copy MD5 Hash: Progress	
Version: 0.9.5 Cancel Read Writ	e Exit
Seconfirm overwrite	X
Writing to a physical device can corrupt t (Target Device: [I:\] "") Are you sure you want to continue?	the device.
😼 Win32 Disk Imager	— — X
-Image File	
	-Device -
F:/FC1e/FLS=3.0.0.5=0F=R1(.1mg	Device
Copy MD5 Hash:	Device
Copy MD5 Hash: - Progress	Device [I:\] ▼
Copy MD5 Hash: Progress	Device [I:\] • 4%
<pre>P:/rcle/FCS-3.0.0.5-0F-KIT.img Copy MD5 Hash: Progress Version: 0.9.5 Cancel Read Write</pre>	Device [I:\] 4% Exit

5 完成烧写提示 Success!

😼 Win32 Disk Imager			
Image File			Device
F:/Pcie/FCS-3.0.0.5-VP-R17.img			[I:\] •
Copy MD5 Hash: Progress			
Version: 0.9.5 Cancel	Read	Write	Exit .
Secomplete			
Write Successful.	444	aller a	

6.将 U 盘插到控台上,使用键盘进行安装。

7.开机**狂按 Fn+F12** 选择 U 盘启动进行安装

GIGABYTE - UEFI DualBIOS
请选择引导设备 × ***
P1: KINGSTON ROU-SC151S373266 Generic Flash Disk B-07 Enter Setup
T and L 移动推择 ESK 使用型认购引导设置 ENTER 引导设备

控台按 Fn+S(下)或者选择第二个选项进行格式化安装。



出现以下情况按键盘上 ESC 键退出 返回以上界面进行操作即可。(有些键盘需要按 Fn+Esc)



8.安装过程中出现提示按回车键即可。

	LOS-INSTALL
	WARNING: ***
	Your disk will be formated. This means all your data will be lost. Please make sure you have a backup of your data before you continue.
	<pre> Yes ></pre>
	LDS- INSTALL
ou are installin System:	IDS-INSTALL ng the follwing system: V3.1.6 R33
ou are installin System: Software: Balance Bate:	ubs-Install ng the follwing system: U3.1.6 R33 U3.0.8 2016 12.06
ou are installin System: Software: Release Date:	UDS-INSTALL ng the follwing system: V3.1.6 R33 V3.0.8 : 2016-12-06
ou are installin System: Software: Release Date:	US-INSTALL ng the follwing system: V3.1.6 R33 V3.0.8 2016-12-06
ou are installin System: Software: Release Date: UMMARY: MODEL:	US-INSTAL ng the follwing system: V3.1.6 R33 V3.0.8 : 2016-12-06 Z3
OU are installin System: Software: Release Date: UMMARY: MODEL: DESTINATION:	US-INSTALL ng the follwing system: V3.1.6 R33 V3.0.8 : 2016-12-06 Z3 : /dev/sda (scsi ata)
Du are installin System: Software: Release Date: UMMARY: MODEL: DESTINATION: SOURCE: ARCHIVE:	US-INSTAIL ng the follwing system: U3.1.6 R33 U3.0.8 : 2016-12-06 Z3 : /dev/sda (scsi ata) /tmp/lds1data/wx//versions/lds1Console_v2.0.tar.gz /tmp/lds1data/wx//versions
ou are installin System: Software: Release Date: UMMARY: MODEL: DESTINATION: SOURCE: ARCHIVE: HD-PARAMS: BOOTPARAMS:	LDS-INSTALL ng the follwing system: V3.1.6 R33 V3.0.8 : 2016-12-06 Z3 /dev/sda (scsi ata) /tmp/lds1data/wx//versions/lds1Console_v2.0.tar.gz /tmp/lds1data/wx//versions 31266648 = 256,ext4,boot 30267,ext4,data -DZ3 -DTIMEOUT=6

选择中文



9.安装完成后机器自动重启,将U盘移除,等待正常进入系统。